



Manual

5 in 1 LED Controller (2.4G)

Model No.: iL5

Features

- This product is made by 2.4G wireless transmitting technology with low consumption and strong ability to resist signal loss.
- 5 kinds of output mode support 5 led strip (Single color/CCT/RGB/RGBW/RGB+CCT)
- Support 2.4G remote control.

Parameters

Model No.: iL5
 Input Voltage: DC12V-24V
 Output: 6A/Channel
 Total output: Max 12A
 RF: 2.4GHz
 Control distance: 30m
 Working temperature: -20~45°C



Output Diagram

Short press "SET" continuously to select output mode, indicator displays different output modes as following diagram.

Indicator	Output
White	Single color
Yellow	Dual white
Red	RGB
Green	RGBW
Blue	RGB+CCT

Setting PWM frequency

Long press "SET" until indicator flashes, short press "SET" continuously to select output mode.


Lowest	Flashing slowly	Flashing quickly	Fastest
250Hz	2KHz	4KHz	8KHz

PWM frequency (Changing different frequency to avoid beep noise from mains).

- ⚠ High frequency only support device with lower wattage, low frequency support device with higher wattage and have better dimming performance.
- Factory default PWM frequency is 4KHz.


2.4G Remote Control

Linking code (2 different solution)




1. Short press "SET" 1 time, short press "1" 3 times within 3 seconds.
2. Power off and power on, short press "1" 3 times within 3 seconds.

⚠ Link is done if the light flashes 3 times slowly.




Cleaning Code (2 different solution)



1. Short press "SET" 1 time, short press "1" 5 times within 3 seconds.
2. Power off and power on, short press "1" 5 times within 3 seconds.

⚠ Cleaning code is done if the light flashes 6 times quickly.



Mini Brightness

1. Long press "OFF" or "O" in group zone 6 seconds until light flashes one time.
2. Short press "OFF" or "O" in group zone to set up 10 kinds of brightness level (1%, 5%, 10%, 15%, 20%, 25%, 30%, 35%, 40%, 50%).

⚠ Short press any button except "OFF" to confirm or step out setting, the master "OFF" can set up all features.

ON/OFF Time

The light status changes gradually (factory default time is 0.5s).

1.5s:
Short press "ON" 1 times and short press "OFF" 5 times within 3 seconds, the setting is done once light flashes 2 times slowly.






0.5s:
Short press "OFF" 1 times and short press "ON" 5 times within 3 seconds, the setting is done once light flashes 2 times quickly.

Dynamic Mode List

Attention: brightness, saturation and speed are dimmable

No.	Dynamic mode
1	Automatical color changing
2	RGB gradual changing
3	Color changing randomly
4	Seven color jumping
5	Color jumping randomly
6	Volcano red
7	Forest green
8	Ocean blue
9	Three color jumping and gradual changing

Connection Diagram



Attention

1. Please cut off power before wiring device.
2. Please check the voltage of power adapter before connecting.
3. Don't disassemble it if you are not expert.
4. Don't use it in metallic or magnetic area.



For more information,
scan QR code

Made in China

