



AC Triac Dimmer (WiFi+2.4G+Push)

Model No.: TD01W

Warm Tips



Please read instruction seriously before installation

Features


- This product is made by WiFi+BLE+2.4G wireless transmitting technology with low consumption and strong ability to resist signal loss.
- Support 2.4G remote control.
- Working with "Tuya Smart" app, wireless dimming, group control, timer function.
- Support Alexa, Google Assistant, Yandex Alice.
- 1-channel output, Max 1.5A.
- Trailing edge phase-cut dimming.
- Supports minimum brightness setting.
- Built-in temperature detection switch.

Parameters

Model No.: TD01W
Input / Output: AC100-240V 50/60Hz
Output Current: Max 1.5A
Output Power: 150W@110V, 300W@220V
Control Signal: WiFi + 2.4G + PUSH
RF Remote Distance: 30m
IP Rate: IP20
Working Temp.: -20~45°C



Connection Diagram



APP Details

1. Download app
2. Registering account
3. Adding device

- 1). Connect Dimmer with power.
- 2). Indicator blinks quickly (2 times per seconds), if indicator doesn't blink quickly.


Method 1

Long press "LINK" 3 seconds.




Method 2

Long press "Push Switch" 30 seconds.



or




3). Connect smart phone with 2.4Ghz WiFi.




4). Click "+"

5). select "lighting" and "light source (BLE+wifi)", finishing the rest steps in app.




4. Dimming Control

Click device to enter into main page.



Voice Control Details

Click "Me", select the third-party service and completed setting.




2.4G Remote Control


Linking code (2 different solution)

Method 1

Short press "LINK" 1 time, short press "I" on the remote 3 times within 3 seconds.



or




Method 2

Press "Push switch" and turn on light, short press "I" on the remote 3 times within 3 seconds.




Link is done if the light flashes 3 times slowly.




Cleaning Code (2 different solution)

Method 1

Short press "LINK" 1 time, short press "I" on the remote 5 times within 3 seconds.



or




Method 2

Press "Push switch" and turn on light, short press "I" on the remote 5 times within 3 seconds.



Cleaning code is done if the light flashes 6 times quickly.



PUSH Dimming

Short press push switch : Turn on/off light

Long press push switch:

- Stepless dimming brightness
- Long press double times to increase or decrease brightness



Attention

1. One push switch can connect with various dimmer, please long press push switch 20 seconds to keep all lights in the same brightness.
2. One push switch only connect with 25 dimmers (max)
3. The cable of push switch can not be over 20m

Attention

1. Please cut off power before wiring device.
2. Please check the voltage of power before connecting.
3. Don't disassemble it if you are not expert.
4. Don't use it in metallic or magnetic area.



For more information,
scan QR code
Made in China

